

200W RMS STEREO AMPLIFIER BT WITH DAB+/FM AMR-200DAB/BK

























- Output power = 200W = 2x 100W RMS @4 Ohms, 0.1% THD.
- Phono Input with Built-In Pre-Amp and RIAA EQ, with Phono Ground (GND) Terminal Connection.
- Full Function Remote Controller in Metallic Finishing with Silicone Rubber Buttons, including MP3/BT Playback controls.
- 6.35mm (1/4 inch) Stereo Headphone-Output Jack built-in.
- 6.35mm (1/4 inch) Microphone-Input Jack built-in.
- Gold Plated A and B Speaker Terminals. Impedance= A/B speaker: 4-8 ohm,A+B speaker: 8-16 ohm.
- High Quality FET Power Amplifier circuit (S/N for AUX∏In > 100dB, S/N for USB+SD/MP3 and Phono∏In >83dB).
- Wolfson 192 kHz/24-bit D/A Converter.
- Treble (10KHz) & Bass (100Hz) independent adjustments +/- 10dB.
- Frequency Response 20Hz 20KHz +/- 0.5dB.
- Channel separation >80dB@1kHz.
- 7 Analog audio inputs: PHONO (MM), CD/SACD, AUX-IN 1, AUX-IN 2, AUX-IN 3, MIC, BT.
- Rec-Out/Line-Out Analog Stereo Output Included.
- LOUDNESS Control button for Audio EQ Enhancement at Night-time.
- DAB+ Digital Audio Broadcast Receiver Built-In.
- FM-RDS Radio Tuner Built-In.
- USB-port + SD-Card slot (in front panel) for MP3 playback, up to 128GB memory readable, with Scrolling id3-Tag song info on display.
- ANTI-VIBRATION Riser Feet with Rubber (Silicone) Pads.
- Digital Rotary Aluminium Controller for Volume/Treble/Bass/Balance/BT-Volume Control with digital
- Bluetooth v5.0 Receiver Built-In with Scrolling Media Info on dot-matrix display and 10M wireless
- Bluetooth v5.0 Transmitter to Stream Wireless Audio to any Bluetooth Compatible Mobile Device and
- Fully Alphanumeric 16 char x 2 lines dot matrix display with White-LED backlighting and Tinted Prism
- Anodized Aluminium front panel (Brushed Hairline Finishing).
- White LED Ambient Light Bar (3D PRISM type) under display on front panel.
- 2 Digital audio inputs: Optical & Coaxial.
- Direct button for EQ Bypass (Direct Power Amplifier Output).
- QUAD Speaker Connections (with Selector for 2x Stereo Speakers A and B).
- Built In DUAL Power Supplies (SMPS for Standby Mode, Toroidal Transformer for Main Operation).
- Hardware ON/OFF Toggle Master Power Switch included.
- Extra Long AC-Power Cord : 2M Length.
- Accessories included: Remote control and AIWA Brand AAA Size Alkaline Batteries x 2pcs, Antenna Wire for Tuner, with Screw-Mount F-Type Connector.
- Dimensions: 430 x 100 x 292mm.

EAN:

8435256898033

MASTER BOX:

Weight: 7.2 kg.

PACKAGING

SKU:

AMR-200DAB/BK



BOX SIZE (L x W x H):

10x29x43 cm



WEIGHT: 9.12



INNER BOX:







